

太阳能控制器10A 12V/24V自动转换

产品名称	太阳能控制器10A 12V/24V自动转换
公司名称	乐清市贝尔奇新能源有限公司
价格	40.00/台
规格参数	名称:太阳能控制器 产品用途:连接蓄电池和太阳能电池板 :
公司地址	中国 浙江 乐清市 柳市镇
联系电话	86-0577-62667676 13506670996 13506670996

产品详情

太阳能控制器10a 12v/24v自动转换

技术参数：

输入电压：12v or 24v 切换

充电电流：10a

dc 负载：10a

充电模式：pwm

specifications:

type	cbk-10	cbk-15	cbk-20
rated charge current	10a	15a	20a
rated load current	10a	15a	20a
work voltage	12 ; 24v ;		
over load, short circuit protection	1.25 rated load current 60sec, 1.5 rated loads current 5sec, over load protection action. 3 rated load current short circuit protection action.		
self-consumption current	6 ma		
charge circuit voltage drop	0.26v		
load circuit voltage drop	0.15v		
over voltage protection	17v; × 2/24v		
work temperature	industry stage : -35 to +55 ; commercialstage-5 to +50		

boost charge voltage	14.6v ; $\times 2/24v$; (keep 10min)(only used when overdischarging)
direct charge voltage	14.4v; $\times 2/24v$; (keep 10min)
float charge voltage	13.6v; $\times 2/24v$;
charge return voltage	13.2v; $\times 2/24v$;
temperature compensation	-5mv/ /2v(boost charge, direct charge, float charge, charge return voltage);
lower voltage indicate	12.0v ; $\times 2/24v$;
over discharge voltage	11.1v (no load) - modified voltage by discharge rate of battery ; $\times 2/24v$;
over discharge return voltage	12.6 v; $\times 2/24v$
over-discharge pressed return voltage	12.4v; $\times 2/24v$
control mode	pwm charge mode; modified discharge voltage by the discharge rate

"太阳能控制器10A 12V/24V自动转换"的产品用途为连接蓄电池和太阳能电池板，名称是太阳能控制器