

高功率保偏耦合器

| | |
|------|-------------------------------|
| 产品名称 | 高功率保偏耦合器 |
| 公司名称 | 上海量青光电技术有限公司 |
| 价格 | 1.00/个 |
| 规格参数 | 品牌:量青光电 型号:耦合器 宽带光源:环形器 |
| 公司地址 | 上海市奉贤区奉城镇东街98号13幢1176室(注册地址) |
| 联系电话 | 021-64778883 17317628715 |

产品详情

高功率微光学型保偏耦合器 High Power PM Filter Coupler 1x2(2x2) PDF资料下载 Applications: Features: EDFA Fiber Optical Instrument Power Monitoring Fiber Sensor Low Insertion Loss High Extinction Ratio、 High Isolation、 High Power High Stability and Reliability Parameter Unit Specification Part No. - LQ-HPPFC-W-PW-AA-R-P-FT-PF-C Type. - 1x2 2x2 Wavelength nm 1310,1550 980,1064 1310,1550 980,1064 Operating Bandwidth nm ± 40 ± 20 ± 40 ± 20 Excess Loss dB <0.7 <0.8 <1.0 <1.2 Uniformity(only for 50/50) dB <0.4 <0.5 <0.6 <0.8 Tap Ratio % $1 \pm 0.2\%$, $2 \pm 0.4\%$, $5 \pm 1\%$, 10% , 20% , 30% , 50% ER type B(both of axis working) - >20 >20 >18 >18 ER type F(fast axis blocked) - >22 >22 >22 >20 Return Loss dB >50 Power handling CW W 1,2,3,5 Fiber type - PM1310,PM1550,PM980 Operating Temperature ° C $-5 \sim +70$ Storage Temperature ° C $-40 \sim +85$ Dimensions mm $5.5 \times L35$ or $L90 \times W20 \times H9.5$ Above specifications are for devices without connector. For devices with connectors, IL will be 0.3 dB higher and RL will be 5 dB lower . and ER will be 2dB lower.The PM fiber and the connector key are aligned to the slow axis. And for F type, fast axis is blocked.

联系人： Michael 李 手机： 173-1762-8715 (欢迎来电) 工作邮箱：
michael@qoptronics.com 咨询QQ: 3191209539 (欢迎咨询) 公司固话： 021-64778883