

感烟探测器 万力达 光电感烟

产品名称	感烟探测器 万力达 光电感烟
公司名称	宁波万力达电子科技有限公司
价格	24.00/个
规格参数	品牌:万力达 型号:NW2101P-RT 类型:光电感烟
公司地址	宁波市鄞州区潘火街道启明路128号
联系电话	87784871 13336671716

产品详情

品牌	万力达	型号	NW2101P-RT
类型	光电感烟	工作电源	DC12V~33V
探测方式	点型	环境温度	-10~60 ()
环境湿度	< 95 (%)		

photoelectric smoke detector

1. function characteristic

this detector is the new generation of intelligence light inductance smoke fire detector. this smoke alarm is designed to give visible warning of a developing fire. the products meet with gb4715-93 standard. model as follows :

w2101p-rt-1m: power off reset , alarm out type : current

base1 : feet: 1: dc+. 3、 4: dc -. 2、 6: nc

nw2101p-rt-1a:auto reset , alarm out type : current

base1 : feet: 1: dc+. 3、 4: dc -. 2、 6: nc

nw2101p-rt-2m: power off reset , alarm out type : current and relay

base1 : feet: 1: dc+. 4: dc -. 2:nc.3:com 6: no(2.3.6relayout)

nw2101p-rt-2a: auto reset , alarm out type : current and relay

base1 : feet: 1: dc+. 4: dc -. 2:nc.3:com 6: no(2.3.6relayout)

2. shape picture of the extenal dimenson of the products

3. specification datas

operating voltage: dc12v~33v

temp. range: -10 ~ 60

humidity range:<95%rh,(do not form revealing)

supervisory current:10~90 μ a

alarm current: < 50ma@24v (with the increasing of voltage)

fire sensitivity:

protection domain: satisfied gb50116-98

led: normal to flash when the alarm light

4. install and wiring

4.1 the detector foundation with indicating light is advantageous for the main entrance direction which the personnel observes, fixed with two m4 from the tapping the foundation in the 86h50 standard buries in advance in the connecting box.

4.2 uses zr-rvs2 × 1.0mm² is flame-resistant double

w2101p-rt02-1m: power off reset , alarm out type : current

base2 : feet:1、 5: dc+.4: dc -. 2:s (ledremote)

nw2101p-rt02-1a:auto reset , alarm out type : current

base2 : feet:1、 5: dc+.4: dc -. 2: s (ledremote)

nw2101p-rt02-2m: power off reset , alarm out type : current and relay

base3 : feet:1:dc+.4:dc-.2:s (ledremote) .3:com.6: no(3.6relayout)

nw2101p-rt02-2a: auto reset , alarm out type : current and relay

base3 : feet:1:dc+.4:dc-.2:s (ledremote) .3:com6: no(3.6relayout)

w2101p02-1m: power off reset , alarm out type : current

base4 : feet:3、 4: dc+.1: dc -. 2:s (ledremote)

nw2101p02-1a:auto reset , alarm out type : current

base4 : feet:3、 4: dc+.1: dc -. 2:s (ledremote)

twists the flexible cord the dc12~33v power source coilin, the negative two-pole meets separately to the foundation 1, on 4 posts, no polarity.

4.3 the foundation indicating light arrow initial direction, clockwise turns on lathe into the foundation installment to be reliable.