

# 日本Alinco DJ-S17M防水对讲机

产品名称	日本Alinco DJ-S17M防水对讲机
公司名称	福州艾林可通信设备有限公司
价格	1100.00/只
规格参数	品牌:日本ALINCO 类型:专业级
公司地址	福州市鼓楼区温泉街道温泉路35号温泉苑5#203单元
联系电话	086 0591 87608119

## 产品详情

品牌	日本ALINCO	型号	DJ-V27T/DJ-V17/47T/EDJ-S17M防水对讲机
类型	专业级	类别	手持台
频率范围	发射频率: 430 - 449.995MHz 接收频率: 410 - 470MHz ( MHz )	射频输出功率	5 ( W )
信道数	200 ( 个 )	理论通讯距离	6 ( km )
工作电压	DC 7.0 - 16.0V ( V )	频率稳定度	+/- 2.5 ( ppm )
电池类型	锂电池	电池理论寿命	26280 ( h )
监听功能	有	外形尺寸	58(宽)x110(长)x36.4(高) ( mm )
重量	280g ( g )	装箱数	20

规格	
一般规格	
频率范围:	dj-v17 / s17t: tx144 - 147.995mhz rx130 - 173.995mhz e: tx/rx 144 - 145.995mhz dj-v27t: tx222 - 224.995mhz rx216 - 249.995mhz dj-v47 / s47t: tx430 - 449.995mhz rx410 - 470mhz approx.e: tx/rx 430 - 439.995mhz
调制:	f3e (fm)
频点:	5,10, 12.5, 15, 20, 25, 30khz
信道数:	200
天线阻抗:	50 欧姆

频率稳定度:	dj-v17 / s17: +/- 5ppmdj-v27/v47 / s47: +/- 2.5ppm
供电电压:	dc 7.0 - 16.0v (ext dc-in)
电流消耗:(标准值)	发射在高功率v/s17 1.4a, v27t 1.6a, v/s47 1.7a接收在 500mw af out: 250mstand-by: v/s17 70ma, v27t 80ma, v/s47 80ma电池省电模式: average 26ma
工作温度:	unit -10digc to 60digc (+14digf to +140digf) battery packs: -10digc to +45digc (+14digf to +113digf)
接地方式:	负极接地
体积:	58(w)x110(h)x36.4(d)mm (2.28"(w)x4.33"(h)x1.43"(d))
重量:	大约280g (9.9oz)带 ebp-65n & 天线
<b>发射部分</b>	
功率输出:	v/s17: 5w (with ebp-65n) 5w (with dc 13.8v) 0.8w (低输出功率)v27t: 5w (with ebp-65n) 5w (with dc 13.8v) 0.8w (低输出功率)v/s47: 4.5w (with ebp-65n) 5w (with dc 13.8v) 0.8w (低输出功率)
调制模式:	可变电抗
静噪抑制:	-60db或更小
最大频偏:	+/- 5khz
mic. 阻抗:	2k 欧姆
<b>接收部分</b>	
方式:	二次变频超外差接收
灵敏度:	-14.0dbu (0.2uv) 或以下
中频:	dj-v/s17:第一中频 21.7mhz 第二中频450khzdj-v/s47 & v27t: 第一中频38.85mhz 第二中频450khz
选择度:	-6db: 12khz 或 -60db: 26khz或以下。
af 功率输出:	500mw (最大) / 400mw (8ohm, 10% 失真)
没有特别通知以上规格不会改变.	
<b>标准配件</b>	
ebp-65 (7.2v 700ma) 锂电池edc-146(t)或 edc-147(别的版本)充电器可弯曲的天线(ea0141 or ea0142)皮带夹子挂绳说明书accessories may differ depending on the versions. please contact your dealer for standard accessories and warranty-policy.	

dj-v/s 17/27/47 free utility 软件下载please be advised that this is a freeware (copyright reserved by alinco, inc). although we have tested this software on our windows 95/98/nt/2000/xp environments and experienced no serious accident during the operation, we are not responsible of any eventual damage caused to your radio and/or pc system by using this utility. sorry, please do not contact us for how to use the software, as this is a very simple editor software. the up-dates will be posted here as soon as available. please uninstall the older version before you install the latest one in case of update. in case you find a bug, please report to export@alinco.co.jp specifying your os.this software enables you to program frequencies, set parameters and save it in your pc for any version of dj-v/s17t/e or v/s47t/e/tfh/r.please be advised that dj-s17/47(without any suffix/japanese models) require different software. it will be posted on alinco"s japanese site soon.dj-v17/s17

clone utility(2.3mb/ver 0.20 beta dec 2006)dj-v47/s47 clone utility(2.3mb/ver.0.10 beta apr 2007)dj-v27 clone utility(2.3mb/ver 0.10 beta june 2007)