

# 雅玛哈MG82CX专业模拟调音台

产品名称	雅玛哈MG82CX专业模拟调音台
公司名称	恩平市圣德尔音响器材厂
价格	150.00/台
规格参数	
公司地址	恩平市恩城茶坑茶盘朗十二巷2号
联系电话	86-07507729869 13631889177

## 产品详情

8输入通道，2单声道, 3立体声

4话筒, 3立体声线路输入

1效果发送/立体声返回

内置spx效果器

低噪声，高精度话筒放大器

开关式幻像电源/插入i/o

内置通道压缩器/3段式通道均衡器

轻巧耐用的机身设计

8 input channels (4 mics + 3 stereo line inputs)

3 band eq (ch 1-5/6), 2 band eq (ch 7/8)

3 busses (stereo + effect), 1 effect send, 1 stereo aux return

spx digital multi effect

xlr connectors

light weight (1.6 kg)

total harmonic distortion总谐波失真 ( thd+n ) : less than 0.1 % (thd+n) 20 hz - 20 khz @ +14 dbu

frequency response频率响应 : 0, +1, -3 db 20 hz - 20 khz @ +4 dbu

hum & noise哼声和噪声 : -128 dbu equivalent input noise/ -100 dbu residual output noise 20 hz - 20 khz, rs = 150  
, input gain = maximum

input connectors输入接口 : mic: 4, line: 2 mono + 4 stereo, ch insert: 2; return: 1 stereo, 2tr in: 1 stereo

output connectors输出接口 : effect send: 1, ch insert: 2, rec: 1 stereo, monitor: 1 stereo, phone: 1

crosstalk串音 : -70 db @ 1 khz

phantom power幻象电压 : + 48 v

input hpf输入高频滤波器 : ch 1-2 and ch 3/4-5/6, 80hz, 12db/oct

ch eq (mono)  $\pm$  15 db (max.) 输入均衡 : high 10 k hz: shelving

mid 2.5 k hz: peaking

low 100 hz: shelving

ch eq (stereo)  $\pm$  15 db (max.) : high 10 k hz: shelving

low 100 hz: shelving

compressor (comp) : control x 1 (gain/threshold/ratio), ch 1-2

internal digital effect内部数字效果器 : 16 program, parameter control foot switch (digital effect, on/off)

led level meter / pre monitor level液晶电平表/监听前电平 : 2 x 7 points led meter (peak, +6, +3, 0, -5, -10, -20 db)  
peak lights if the signal comes within 3 db of the clipping level.

peak indicators峰值表 : red led turns on when post eq (st ch: or post mic ha) signal reaches -3db below clipping  
(17dbu).

power supply adapter电源转换 : pa-10: ac 38vct, 0.62a, cable length = 3.6m

power consumption功率消耗 : 21 w

dimensions 尺寸(w x h x d) : 256.6 mm x 62.2 mm x 302.5 mm

net weight净量 : 1.6 kg