

12	zx37-4.2	37	4.2	0.84	0.84	0.84	0.84	0.84	zh-2-3
13	zx37-5.6	32	5.6	1.12	1.12	1.12	1.12	1.12	zh-2-4
14	zx37-8	27	8	1.6	1.6	1.6	1.6	1.6	zh-2-5
15	zx37-11	23	11	2.2	2.2	2.2	2.2	2.2	zh-2-6
16	zx37-16	19	16	3.2	3.2	3.2	3.2	3.2	zh-2-7
17	zx37-2	53	2	0.4	0.4	0.4	0.4	0.4	zh-3-1
18	zx37-2.5	47	2.5	0.5	0.5	0.5	0.5	0.5	zh-3-2
19	zx37-3.3	41	3.3	0.66	0.66	0.66	0.66	0.66	zh-3-3
20	zx37-4	37	4	0.8	0.8	0.8	0.8	0.8	zh-3-4
21	zx37-5	34	5	1	1	1	1	1	zh-3-5
22	zx37-6.6	29	6.6	1.32	1.32	1.32	1.32	1.32	zh-3-6
23	zx37-7	28	7	1.4	1.4	1.4	1.4	1.4	zh-3-7
24	zx37-9	25	9	1.8	1.8	1.8	1.8	1.8	zh-3-8
25	zx37-11	23	11	2.2	2.2	2.2	2.2	2.2	zh-3-9
26	zx37-14.5	20	14.5	2.9	2.9	2.9	2.9	2.9	zh-3-10
27	zx37-19.5	17	19.5	3.9	3.9	3.9	3.9	3.9	zh-3-11
28	zx37-28	14	28	5.6	5.6	5.6	5.6	5.6	zh-3-12
29	zx37-35	13	35	7	7	7	7	7	zh-3-13
30	zx37-44	11	44	8.8	8.8	8.8	8.8	8.8	zh-3-14
31	zx37-58	9.8	58	11.6	11.6	11.6	11.6	11.6	zh-3-15
32	zx37-80	8.4	80	16	16	16	16	16	zh-3-16

技术性能参数

zx37系列电阻器安全可靠，具有耐腐蚀、无感应电阻值稳定（误差为7.5%）。使用寿命长等优点，电阻器的功率可达5.6kw，适用于各类绕线型号的电动机的配套组合。

外形及安装尺寸

杰胜电气销售中心-----联系方式:

电话/传真:0577-27861701

手机:13676571823