

热销非洲/加纳 T2+S2 Combo 机顶盒

产品名称	热销非洲/加纳 T2+S2 Combo 机顶盒
公司名称	深圳市沃佳科技有限公司
价格	95.00/台
规格参数	品牌:OEM 型号:T2+S2
公司地址	深圳市龙华新区观澜南大富社区大布头村东33-7号2楼
联系电话	85242913 13554918783

产品详情

dvb-t2+s2 combo receiver

?.general

1.produce type name

produce type number dvb-t2+s2

2.main features

stb type	t2+s2
main chipset	sunplus sphe1505b
sdram memory	32x16mbit ddr2 frequency1066
flash memory	32mbits
demodulator type	avl6862ta chip set
tuner type	rafael r848 board tuner design
interface	hdmi.cvbs.232,audio l/r?ypbpr?coaxial s/pdif.need
usb 2.0	embedded host
smpps type	smpps

pcb	2 layer fr4
4.notice	
rohs	need
certification	ce authentication by ccs
?.software features	
1.software general features(dvb-2)	
mpeg4	fully comply with dvb-t2/s2, mpeg-2/4 h.264 standard
pan/ntsc	automatic pal/ntsc conversion
channels number	4000 channels memory capacity
favorites	8 different favorite groups selection
osd language	english french czech danish russian german italian dutch d
epg	fully support to 7 days electronic program guide(epg)
picture	support?jpg? jpeg?jpe?bmp?png
channel search	channel search in automatic, manual and network search
channel edit	various channel editing function(favorite,move,lock,skip,del
parental lock	parental control for channels
easy menu	plug and play installation, with an ease to use menu system
softupgrade	software upgrades through usb
time set	time set by gmt offset automatic and manual,summer time s
teletext	support osd/vbi formart
subtitle	subtitle support
searching time	high speed scan
save channel	automatic save for last channel
lcn	support logic channel number(lcn)
power	auto power down
ant-ana ctrl	active antenna power supply control
?.electric performance	
1.dvb-t2 tuner demod	

demodulator type	avl6862ta chip set
tuner type	rafael r848 board tuner design
input rf frequency	48~858mhz
bandwidth	6mhz,7mhz,8mhz
rf tuner & dvb-t2 channel complied standard	etsi en 302 755 v1.1.1 (2009-09)input impedance 75ohm
sensitivity level	- 20~ - 83dbm
demodulation	cofdm
mode ifft	1k, 2k, 4k, 8k, 16k, 32k
fec mode	ldpc + bch 1/2, 3/5, 2/3, 3/4, 4/5, 5/6
guard intervals	1/4,19/128,1/8,19/256,1/16,1/32,1/128
constellation	qpsk, 16qam, 64qam, 256qam
scattered pilots	1%, 2%, 4%, 8% of total
continual pilots	0.35% of total
typical data rate (uk)	40 mbit/s
max data rate (@20 db c/n)	47.8 mbit/s
required c/n ratio (@22 mbit/s)	8.9db
dvb-t2 input profiles plp	support single and multiple plps
ant power	max 200ma

dvb-s2 tuner demod

demodulator type	avl6862ta chip set
tuner type	rafael r848 board tuner design
input rf frequency	950~2150mhz
rf tuner & dvb-t2 channel complied standard	etsi en 302 307 input impedance 75ohm
sensitivity level	0~ - 86dbm
demodulation	qpsk, 8psk 16ask 32ask
fec mode	1/4,1/3,2/5,3/5,2/3,3/4,4/5,5/6,8/9,9/10
scattered pilots	1%, 2%, 4%, 8% of total
continual pilots	0.2, 0.25 0.35

typical data rate

1~55 mbit/s

ant power

max 300ma

4.environment

input voltage	ac 90~250v/50hz/60hz
consumption	max 12w
temperature	0~40℃
humidity	<95%

1.we accept payment via tt (bank transfer), western union, and paypal.

2.we only accept bank transfer for large orders. for small order, you can pay via western union or paypal.

dhl,ups ,fedex express, or by air /by ocean ,or as customers' requirment.

1.all electronic products (included brand ones) may have problem after used for a period of time.

2.we provide 1 year warranty for all products. please contact me if you need our detail warranty term