

2?????

??

3?????

??;

??

4?????

??;

?50-60kps??

5?????

??

6?????

??

?????

????????????????UPS????????????????????????????????ABS????????????????10?(25?) ?

?????GFM-E???????

????? ?????????????????????UPS?? 1.?????????15?(25?)2.ABS?????3.AG M????????4.?????

电池型号	额定电压(V)	额定电压(C10 Ah)			外形尺寸(mm)			宽
		C10	C3	C1	长	宽		
GFM-200E	2	200	150	110	94.5	184.5	360.5	372
GFM-300E	2	300	225	165	123	184.5	360.5	372
GFM-400E	2	400	300	220	166	184.5	360.5	372
GFM-500E	2	500	375	275	194.5	184.5	360.5	372
GFM-600E	2	600	450	330	223	184.5	360.5	372
GFM-800E	2	800	600	440	154	229	555	566
GFM-1000E	2	1000	750	550	186	229	555	566
GFM-1200E	2	1200	900	660	225	229	555	566
GFM-1500E	2	1500	1125	825	265.5	229	555	566
GFM-2000E	2	2000	1500	1100	349	233	555	566
GFM-800EA	2	800	600	440	280	184.5	360.5	372
GFM-1000EA	2	1000	750	550	339	190	360.5	372
GFM-2000EA	2	2000	1500	1100	328.5	363	362	374
GFM-3000EA	2	3000	2250	1650	496	363	362	374

