



??	0?200000lx
??????	390nm?780nm
????	RS485
?????	Modbus-RTU??
????	Modbus-RTU?? ????1??????????16? 00??????16? 01????
????	9600?1?N??????????
????	????+ ??GND ??RS485A ??RS485B
??	?25mW@5V
????	DC 4.50?13.2V
????	0?100RH

????

-40?80?

????????????????????

??	??	????
NHZD10AU	0?2000 lx	????
NHZD10BU	0?20000 lx	????
NHZD10CU	0?200000 lx	????
HNZD10CR	0?200000 lx	RS485??
???????	????????????????4-20mA?RS485????????????3? ?????????	

???????

?????

????????????51mm????????4.5mm????????????4??

????????

????????????????????????????

????????????????????????????

????????????????

????????

??

????????????????????????????

????????????????????????

????????????????????

??????

?????

01 04 00 00 00 02 71 CB

??????

01 04 04 00 00 01 AC FA 69 ????428lx

??????

?????—?????????????—?????????????

-??LUX?lx????????????????LUX?lx??1?????1 lm?????????????1 m2????  
??????

????????????????LUX

???0.004-0.02

???0.02-0.3

?????5-50

?????50-500

?????100-1000

?????????????1000?000

?????????????50-60

?????????????1400

??????? ????027-8181-2592 150-7141-5010

QQ?1875652916

???[neng-nh@qq.com](mailto:neng-nh@qq.com)

? ??[www.nengh.com](http://www.nengh.com)