

HOP-EU04F2V

产品名称	HOP-EU04F2V
公司名称	深圳市昊海通信技术有限公司
价格	380.00/台
规格参数	
公司地址	深圳市福田区滨河大道上沙创新科技园15栋8楼
联系电话	18681593820

产品详情

????

hop-eu04f2v????????????????????gepon????????????????????????????????????pots????????802.3ah????????gepon onu
????????????????????voip ?????????????????????????????????????olt????????epon????????????????????????????????????4?1
0/100m????????2?pots??fith???????

???????

--

1 gepon interface

4 ethernet lan port(10/100 base-t auto-sensing)

2 pots

1 power supply port

1 reset to factory default button

led

??????

????epon

onu

4fe+2pots ??????????????gepon??????32????????????????????????20??

????????

hardware and interface

1 gepon interface

4 ethernet lan port(10/100 base-t auto-sensing)

2 pots

1 power supply port

1 reset to factory default button

led

ethernet port

port auto negotiation

mdi/mdix

802.3x flow control

per port ingress/egress rate limit

storm control

mac limit per port

port isolation

rstp

port mirror

vlan

802.1q vlan

svl

vlan id:1-4094

ctc vlan

multicast

igmp snooping

128 multicast entry

ctc controllable snooping

qos

classification: da mac,sa mac, vlan pri,vlan id, ether type, da ip, sa ip,802.1p/dscp/tos

scheduling: sp/wrr/sp+wrr

pon

compatible with ctc specification

compatible with 802.3ah

4 queue and sp scheduling

support dying gasp

oam

telnet

snmp

dhcp client

firmware remote & local upgrade

config file remote & local upgrade and download

voip

support sip/mgcp/h.248

compatible with hw/zte/asb softswitch??????40 ???

support itu-t g.711?g.723.1?g.729

support ec (echo canceler),max 128ms

???/????????t38 ????

??rfc2833 ??rfc2833?????md5 ?????????????????????????????

?? ?pots ?????????????????????

7x24 ?????0.01?

??pots ?gr909 ??????

mac address table

8k mac table

wire speed mac learn

static mac address entry

black list

configurable mac aging time

???????

???????

epon??:	ieee802.3ah
?????????:	1 gbps
?????????:	1 gbps
?????:	1 sc/upc (??)
?????????:	4 (rj-45?10/100mbit/s?mdi/mdix???)
pots??	2 rj11??????????/????

??????????

?????????:	100v?240v ac?50hz?60hz
?????:	12v dc?1.0a
?????:	<=7w

?????:	-10?c?55?c
?????:	5%?95%????
?????:	-40?c?75?c
?????:	75%????
??:	160mm(?)×115mm(?)×32mm(?)
??:	0.50kg

????????<, /span>

??	??ce?rohs6?ccc???
emc/emi	??vcci class b?fcc part 15 b??
??	??ul 60950????
???????????	??itu-t k.21??