

usb?????pc???????????????????? ?
 ?????????100????????200???? ? ?????sci?sce????????????sci/sce??

caipu?? cs-600a ?????????

????	cs-600a
????	d/8(????8????) scs????(?????)?etc(?????) ??sci(????????)/sce(????????)?????? (??cie no.15?iso 7724/1?astm e1164?din 5033 teil7?jis z8722 condition c ??)
?????	?40mm?alvan????????
????	cleds(????led??)
???	?????????
???????	400-700nm
????	10nm
???????	5nm
?????????	0-200%
?????????	0.01%
?????	2°/10°
????	a,c,d50,d55,d65,d75,f1,f2,f3,f4,f5,f6,f7,f8,f9,f10, f11,f12,dlf,tl83,tl84,nbf,u30,cwf
??	????/????????????/????/???????????? ?????????????????????????????????????
???????	???
????	1?
????	?8mm/4mm
????	cie- l*a*b,l*c*h,l*u*v,xyz,yxy,???,hunterlab,munsell mi,cmyk
????	?e*ab,?e*ch,?e*uv,?e*cmc(2:1), ?e*cmc(1:1),?e*94,?e*00,?eab(hunter),555, ????
???????	wi(astm e313-00,astm e313-73,cie/iso,aatcc,hunter,taube berger stensby),yi(astm d1925,astm e313-00,astm e313-73),tint(astm e313,cie,ganz),??????milm,?? ??,????,iso??,8???,a??,t??
???	?????????????0.08%?? ??????e*ab 0.03(???,????5s????30?????)?????0.05

????	????????????10000??7.4v/6000mah
??	usb
????	20000?????
???????	10?300??
???	?e*ab 0.2??(bcra??12?????????)
??	181*73*112mm(l*w*h)
??	?550g(????)
???	?????
???????	0~45??????80% ???(?35°c?)??????
???????	-25°c ?55°c??????80% ???(?35°c?)??????
????	?? ????????????????????????????????????
????	????????????????????????
????	??
uv??	??uv??