



usb?????pc???????????????????? ?  
 ?????????100????????200???? ? ?????sci?sce????????????sci/sce??

caipu?? cs-610a ?????????

????	cs-610a
????	d/8(????8???? scs????????????????etc???????? ??sci????????/sce???????????????????? ???cie no.15?iso 7724/1?astm e1164?din 5033 teil7?jis z8722 condition c ???
?????	?40mm?alvan?????????
????	cleds(?????led???)
???	????????400-700nm
??????	
????	10nm
??????	5nm
????????	0-200%
????????	0.01%
?????	2°/10°
????	a,c,d50,d55,d65,d75,f1,f2,f3,f4,f5,f6,f7,f8,f9,f10, f11,f12,dlf,tl83,tl84,nbf,u30,cwf
??	???/????????????/????/???????????? ?????????????????????????????????????
??????	?2?
????	1?
????	?8mm/4mm
????	cie-l*a*b,l*c*h,l*u*v,xyz,yxy,???,hunterlab,munsell mi,cmyk
????	?e*ab,?e*ch,?e*uv,?e*cmc(2:1), ?e*cmc(1:1),?e*94,?e*00,?eab(hunter),555,????
??????	wi(astm e313-00,astm e313-73,cie/iso,aatcc,hunter,taube berger stensby),yi(astm d1925,astm e313-00,astm e313-73),tint(astm e313,cie,ganz),?????milm,????,????,iso??,8???,a??,t??
???	????????????0.08%??
	?????e*ab 0.02????,????5s????30????????????0.04
????	????????????20000??7.4v/6000mah
??	usb,??
????	40000?????

