

sdi????????????? iec169-8 ???bnc???

??????

????????????????????????????????????0?1.5??

??????

?????????????imarv???scaler?????????????

?????

??3g-sdi?hd-sdi?sd-sdi

?????????

??isl59830????????????????????300??

??????

??

??????

????????? lock ?????????????????????? prot ???

rs-232?rs-422?rs-485

?????? rs-232 ?????????????????? rs-422?rs-485 ???

tcp/ip?????????

???????????????? tcp/ip ?????????????????????????????????

??????

????110v?260v/ac 50/60hz ??????????????????????

??????

????32????????????????????????????/rs232/pc????????????????????????????

??	
??	200mhz (-3db),???0 - 10mhz @ ±0.1db?0 - 100mhz @±0.6db
????????????	-60db @10 mhz? -50db @100 mhz
???????	0.1%, 3.58-4.43mhz
???????	<1.28?, 3.58mhz

??????	< -80db@100khz???
????	ntsc3.58?ntsc4.43?pal?secam?hdtv
????	?????????
????	
??	rca???
????	0.3v—0.4vp-p
??/????	?????0.5v ~ 2.0v p-p
??	75 ?
????	<-50db@5mhz

????????

15mv

????

??

rca???

??

75 ?

????

<-50db@5mhz

????

??±5mv

????

????

????

??/????

rca???

????	20 hz ~ 20 khz
????? ??	0.03% @ 1 khz ????????
????s/n?	>100db
???????	>90db @ 1 khz
???????cmrr?	>85db @: 20 hz ~ 20 khz
????	???
???????cmrr?	>85db @: 20 hz ~ 20 khz
??	??>10 k?????50 ?
???????	+19.5dbu

????	±0.1db
???????	+19.5dbu
????	
???????	rs-232 ??
???????	????9600, ?????8?, ?????1, ????????
?????????	2 = tx, 3 = rx, 5 = gnd
?????	?yucoo?
????	
??	100vac ~ 240vac, 50/60 hz, ????????

??	????????: -20° ~ 70°c
??	????????:10% ~ 90%?
??	20w
????	482mm???x 210mm??? x 45mm???
????	19????? 1u??
????	3.0kg
??????????	48,000 ??
????	????????????????????????????????