

# 深圳世界之光供应相变LED工矿灯400W

产品名称	深圳世界之光供应相变LED工矿灯400W
公司名称	深圳世界之光科技有限公司
价格	面议
规格参数	品牌:世界之光 型号:WL-HB400W 功率:400W
公司地址	深圳市龙岗区坂田街道长坑四区
联系电话	0755-28222243 15899888930

## 产品详情

### SPECIFICATION

(?????)

??????

1.???LED??

2.????????????????????????5????????

3.????????????400WLED????????????????60%?

??????

??

??????

?????LED 400W??

??????????????????,??

????????????????????????????

????????????????????????????

??

??

??

?????????



Input voltage	AC85V-265V	Picture
Frequency range	50HZ-60HZ	
Total harmonic distortion	9%	
Power factor	0.90	
LED Working voltage	DC30-36V	
LED quantity	1/4PC	
LED consumption	380W	
System consumption	400W	
LED luminous efficiency	90-100LM/W	
LED	Warm white	38700LM
LED luminous	Pure white	38750LM

	??Cold white	38800LM
???? Lamp's efficiency	>91%	
Average illuminance	??(height)? 5M	?300LUX
	??(height)? 8M	?200LUX
	??(height)? 10M	?120LUX
Illuminance area	??(height)? 5M	?2M ??
	??(height)? 8M	?3M ??
	??(height)? 10M	?5M ??
?????Illuminance uniformity	?0.8	
Color temperature	??Warm white	?2700-3200K
	??Pure white	?5500-6500K

	??Cold white	7000-10000K
????	??WW	Ra?78
Color rendering index	??/??PW/CW	Ra?85
????Light distribution	??/????	
???? Light design	LED+???????	
LED ????Junctiontemperature	? 75?	
??????Workingtemperature	-40?—+50?	
??????Storage temperature	-25?—+65?	
????IP Grade	IP65	????Light distrib
??????Working life-span	?50,000H	

?????	??Brown	L ??
Connect wire	??Blue	N ??
	??/??Yellow/Green	G ??
??????Color of lamp shell	??/??Black or Silver	
?????Certificate	CE, RoHS	
???Beam angle	120?	
????/??Lamp weight : G.W./N.W.	9.6Kg	
?????MM?Size	260*300MM	

?????

1. ?????????AC 85V?265V 50/60Hz???????????????? 2. ???

???????

1. ????????? M20 ???

2. ????????????????

3. ????????????

4. ????????????????????????

5. ????????????????????????????

6. ??????????????????????

7. ??????????0.75MM2???

???????

1. ??????????????

2. ?????????????????????????????????

3. ?????????????????????????????????

4. ?????????????????????????????????

5. ?????????????????????????????AC ?????????????????????“L”? ?????????“N”, ?????????“ ”?DC ??????????  
????????????????????????????????

?????????

???????

????????????????????????LED ???

??

?????????????



