

5?????h.264????????fec????????????????????????????????

6???fpga????????isp ?????????????????????????????????????

7???bfcptip????????sip????????????????????????????????

8????????????12????????

9????????????????????

GVC3200 ????

????	sip rfc3261, bfcptip (pending), rtp/rtcp, http/https, arp, icmp, dns (a record, srv, naptr), dhcp, pppoe, ssh, tftp, ntp, stun, lldp-med, ldap (pending), tr-069, 802.1x, tls, srtp, tcp/ip/udp, ipv6 (pending), fec, fecc, (pending: h.323, h.245, h.225, h.235, h.241, h.460)
???	200???, 1/3?? cmos, 1920hx1080v@30fps???
??	12?????, +/- 23°????? +/- 90°????? 70°(w)* - 6.3° (t) ??????
????	1x rj45 10/100/1000 mbps?????
wi-fi	?? 2.4ghz?? 5ghz ?? wi-fi (802.11a/b/g/n)
??	?? 4.0 edr????
????	3??? cec???????? 1080p?hdmi ??
????	1?vga??? 1?????? 1080p?hdmi ??
??/???	?????/?????? mic?????????/???? pengding?
??	????????????????
????	?? 2.0 usb??? sd????????????????????
????	128x32???? oled
??????	g.711?/a, g.722 (wide-band), g.726-32, ilbc (pending), opus, g.722.1, g.722.1c (pending), in-band and out-of-band dtmf (in audio, rfc2833, sip info)
??????	h.264 bp/ mp/ hp???????? 1080p????? 30fps?????? 4mbps
??????	1080p from 512 kbps, 720p from 384 kbps, 4sif/4cif from 128 kbps, sif/cif/qsif/qcif/sqsif/sqcif from 64 kbps
??????	???vga?svga?xga?wxga?wxga?sxga?1440x900?720p?1600x1200?1080p?hdmi???? 60fps???? 1280x720?1920x1080
?????	720p?1080p
mcu	????4?1080p????5?720p????9?vga??
????	??bfcpt????(1080p 30fps)???(1080p 15fps?720p@30fps)????
????	????????aec????????ans????????agc????????plc????????cng?/????vad?
????	fec????????????????????pending?
????	????????????voip??sip????skype?skype for business?google hangouts?
????	??9????????????????xml? ldap??fail-over??
??????	????????/????????????api/sdk?????
????	????4.4????????provisioning????
qos	??????802.1q?802.1p?????tos?diffserv?mpls?qos
???	????????????????md5?md5-sess

	based???256?aes???????128?256?srtptls?????https?802.1x???????
?????	??
??/?	??tftp/http/https?http????????????tr-069?aes???xml????????????????
??/????	????????????100-240vac 50-60hz????12vdc/5a (60w)
????	gvc3200????????usb???/????????????????????????1.5???usb????5????????4?hdm? ????1?1.5?,2?3?,1?5????2?aaa?????????????????gpl???
??????????	???0°c?40°c????-10°c?60°c????10??90?????
????	fcc: part 15 (cfr 47) class b; ul 60950 (?????), part 15c, part 15e.407, part 2.1091ce: en55022 class b, en55024, en61000-3-2, en61000-3-3, en60950-1, en62479, rohs, en301893,en62311rcm: as/nzs cispr22/24; as/nzs 60950; as/nzs 4268