



????

?????1)

5 ... 320bar

????

0bar

??????

5 ... 1000 mm2/s

???????? 2)

0 ... +60 °c

??????

??

-10 ... +60°c

?? (???)

0 ... 95% rel.

??????

??

-20 ... +60°c

?? (???)

0 ... 95% rel

?????

???????????????

????

????????????????????????????????????pvc?????

????

??

24vdc

??????

8a

??????????

??

100 ... 240vac (50/60 hz)

????

?? 4a

???? 24vdc

?? 221w

????

????

6900 mah

????

< 1h

????????????(????????????????????????)

> 24h

????????

?? iso 4406:1999

???

0 ... 24?? (oz)

??????????

10 ... 22?? (oz)

????

4, 6, 14, 21?m (c)

??????????

???????

1 ... 7

????

0 ... 100%

??? 100 ... 800000ps/m

?? -20 ... +120°C

????

????? (???????) ± 1 ?? (oz)

?????? 3) ± 0,015

???? 4) ± 3

% ???

??? typ. < 10 / ± 200 % ??? /  
ps/m

?? ± 2 % ???

??????

??? (???????) ??? m16x2

??? (???)cpc-lc ??

??? cpc-lc ??

?? usb-b, sd-(sd ?sd-hc in  
fat/fat16/fat32-????)

?????????? 1250 ?? (???)

?? < 10 kg

????

??????100-240v????????????????????