

4G模块通信模块移远安防车联网EC20-C

产品名称	4G模块通信模块移远安防车联网EC20-C
公司名称	深圳市晟泰威视科技有限公司
价格	280.00/pcs
规格参数	品牌:移远 型号:EC20
公司地址	深圳市南山区朗山路7号南航大厦10D
联系电话	075526419480 13530469596

产品详情

?? EC20-E Mini PCIe

FDD LTE: B1/B3/B5/B7/B8/B20

UMTS: B1/B5/B8

GSM: 850/900/1800/1900MHz

EC20-A Mini PCIe

FDD LTE: B2/B4/B5/B12/B17

UMTS: B2/B4/B5

GSM: 850/1900MHz

EC20-C Mini PCIe

FDD LTE: B1/B3/B8

TDD LTE: B38/B39/B40/B41

TDSCDMA: B34/B39

UMTS: B1/B8

GSM: 900/1800MHz

LTE?? 3GPP E-UTRA Release 9

???? 1.4/3/5/10/15/20MHz

?? DL MIMO 2x2, supports Rx-diversity

???? 3.0V~ 3.6V , 3.3V Typ.

???? -40°C ~ +80°C

???? 51.0 x 30.0 x 4.9mm

?? Approx. 9.8g

AT???? 3GPP TS27.007 ??????AT??

????

?? LTE LTE-FDD Max 100Mbps (DL) Max 50Mbps (UL)

LTE-TDD Max 61Mbps (DL) Max18Mbps (UL)

DC-HSPA+Max 42Mbps (DL) Max5.76Mbps(UL)

UMTSMax 384Kbps(DL) Max 384Kbps(UL)

EDGEMax.236.8 Kbps (DL)/ Max.236.8 Kbps (UL)

GPRSMax.85.6 Kbps (DL)/ Max.85.6 Kbps (UL)

?? ?????? HR, FR, EFR, AMR, AMR-WB

????????????????

eCall* ?????????

VoLTE* ?????VoLTE(Voice over LTE) (??)

?? TCP*/UDP*/PPP/FTP*/HTTP*/SMTP*/MMS*/ SSL*

????

??USB SerialWindows XP, Windows Vista, Windows 7,Windows 8/8.1, Windows CE5.0*/6.0*/7.0*,Linux 2.6 or later, Android 2.3 /4.0/4.2/4.4

RIL Windows CE6.0*,Windows Mobile 6.1*/6.5*,Android 2.3/4.0/4.2/4.4

NIDSWindows XP, Windows Vista, Windows 7,Windows 8, Windows?CE5.0*/6.0*/7.0*

DFOTA

??????

GNSS* GPS/GLONASS (Optional)

????

????? Class 3 (23dBm±2dB) for LTE FDD

Class 3 (23dBm±2dB) for LTE TDD

Class 3 (24dBm +1/-3dB) for TD-SCDMA

Class 3 (24dBm +1/-3dB) for UMTS

Class E2 (27dBm±3dB) for EDGE 850/900MHz

Class E2 (26dBm +3/-4dB) for EDGE

1800/1900MHz

Class 4 (33dBm±2dB) for GSM 850/900MHz

Class 1 (30dBm±2dB) for GSM 1800/1900MHz

?? 5.5mA@Sleep,Typ

??? LTE B1:-97dBm(20M)

LTE B3:-96dBm(20M)

LTE B5: -99dBm(10M)

LTE B7: -97dBm(20M)

LTE B8: -98dBm(10M)

LTE B20: -96dBm(20M)

UMTS B1: -110dBm

UMTS B5: -112dBm

UMTS B8: -111dBm

GSM 850: -111dBm

GSM 900: -110dBm

GSM 1800: -109dBm

GSM 1900: -109dBm

??

USB 2.0 Device??, 480Mbps ??(12Mbps)??

PCM 1???????(???????????)

USIM 1.8V/3V

LED_WWAN# ??????

W_DISABLE# ??RF??

?? x1

PERST# ????

?? TDB