

5????????????????FFT???????????????????? 7????????????PC????????????

VA-12??????????

????CE??EMC??2004/108/EC? ??RoHS????????????WEEE?? ?????? ??????1?
????BNC?CCLD 18V 2mA(CCLD 24V 4mA ??) ?????????????PV-57I ??????
????????1.00-9.99mV/(m/s2) PV-57I ?????1,3.16,10,31.6,100,316,1000m/s2 (rms)
????3.16,10,31.6,100,316,1000,3160mm/s (rms) ???0.089,0.283,0.894,2.83,8.94,28.3,89.4mm(EQP-P)
????PV-57I)????0.02-1000m/s2 (rms) ???0.1-3160 mm/s (rms) ???0.003-89.4 mm (EQp-p)
????????????1Hz-20 kHz ???3 Hz-3kHz ???3 Hz-500 Hz ??????1kHz-20kHz
????????1Hz????????3Hz?10Hz?1kHz ??????1kHz? kHz?20kHz ?????????1kHz ?????????20kHz
A/D???24? ??????110dB

????512 1024 2048 4096 8192 ?????????????? ?????????????????????
?????100HZ?200HZ?500HZ?1kHz?2kHz?5kHz?10kHz?20kHz ?????????10????????????? ???????????
X????x1,x2,x4,x8,x16; Y????????1024? ?????????????? ?????????????????? ?????TFT
LCD????????240*320 ?????????????? ?????LED????????? ?????SD????2 GB? ?????
1????????1000????????????100????? ?????????????????????????????????5?????
BMP????????????BMP??? ?????????????????????????????????????? ?????????????????????????
??/????AC????????????????USB?? ??AC???NC-99???8?IEC R6????AA???23?????????????
?????12????????145????????????????? ?????????-10?+50?90?RH????????? ???214 (H) x 105 (W) x 36 (D)
mm; 2????????850g????????????PV-57I???

VA-12??????????

??VA-12????? 1? ?????PV-57I 1? ???IEC R6? 8? ?????1? ?????1? ?????VA-12S1? ???1? ???1?
????????1?

??????http://www.isc-bauer.com/

?????https://rsland.1688.com/

https://isc-bauer.taobao.com/

?????13923724710

13823138243