

ü SCPI?????????

ü ??????GUI

ü ???????

?????

ü ??????????

ü DWDM?????

ü OSNR??

ü ???????

ü ??????

ü ?????

??????

???????
??????????
??????
???????
????????
????????????????????15.600?
????????????????????
????????
?????????
?????????
?????????

191.25 – 196.125 THz 1528.5 – 1567.5 nm

312.5 MHz 2.5 pm

1.7 GHz 13.6 pm

+/- 1 GHz 8 pm

1 Update / s

-50 – +23 dBm -70 – 3 dBm

0.4 dB

??????	+/- 0.7 dB
??????	> 45 dB
?????	> 35dB
??????	FC/APC
????/??	3.3V TTL (SMA female)
????	USB, Ethernet
???? ???	0 – 40 °C -20 – 60 °C
????	
?????H x W x D?	44 x 205 x 270 mm 1.7 x 8 x 10.6 inch
??	< 3 kg
????	100-240 VAC, 80VA, 50/60Hz

?????

ID-OSA-MPD-00	OSA??
ID-OSA-ACC-RM-01	19?????????????1 HE 1???
ID-OSA-ACC-RM-02	19?????????????1 HE 2?????2?????1?

