



????????2?

?????35 Hz to 20KHz

???????M24mm??80???????1.0?

??????? -20?60? ?? 10?90%RH

??????? -20?80? ?? 10?90%RH

???????????

4-20mA?????WS700A

??V+???V-???????????????

0-5V?????WS700B;

??V+???V-???????????????????

0-10V?????WS700C;

??V+???V-???????????????????

???????????????

4-20mA?????

$$dB = (Ix - 4) * 6.25 + 30 \quad Ix = (I1 + I2 + I3 + \dots + I100) / X \quad X = \dots$$

0-5V?????

$$dB = Vx * 20 \quad Vx = (V1 + V2 + \dots + Vx) / X \quad X = \dots$$

0-10V?????

$$dB = Vx * 10 \quad Vx = (V1 + V2 + \dots + Vx) / X \quad X = \dots$$