

4K*2K HDMI分配器1X2

产品名称	4K*2K HDMI分配器1X2
公司名称	深圳市鑫浩悦科技有限公司
价格	45.00/台
规格参数	品牌:中性 型号:XHY-SP04
公司地址	深圳市宝安区西乡街道航城大道172号安乐工业区B1栋4楼
联系电话	18170576900 15112336262

产品详情

USER MANUAL

HDMI Splitter 1x2

Enjoy the vivid world!

INTRODUCTION

HDMI Splitter 1x2

The HDMI Splitter 1x2 uses a single HDMI source, accessing to multiple HDMI sinks. The splitter allows one HDMI device to be split easily to two HDMI compatible monitors or projectors. The splitter can also be placed at the end of a long HDMI cable to regenerate the HDMI signal. The HDMI Resolution up to 3840x2160/30Hz.

FEATURES

1. Support HDMI 1.4b
2. Support Full 3D
3. Support HDMI resolution up to 3840x2160/30Hz
4. Support the max baud rate of 3.4G and max bandwidth of 340Mhz
5. Support deep color 8/10/12bit
6. Support input up to 10metres AWG26 HDMI standard cable length, output up to 15metres AWG26 HDMI standard cable length
7. Displaying single source, multi-output high-definition signal source from DVD player A / V receiver, set-top box
8. 5V / 1A power adapter

SPECIFICATIONS

HDMI version	HDMI 1.4b
HDMI resolution	UP TO 3840*2160/30Hz
Support video color format	8/ 10/12bit deep color
Support audio format	DTS-HD/Dolby-trueHD/DTS/Dolby-AC3/DSD
Max bandwidth	225MHz
Max baud rate	2.25Gbps
Input cable distance	10m AWG26 HDMI standard cable
Output cable distance	15m AWG26 HDMI standard cable
HDMI input	1 HDMI
HDMI output	2 HDMI
Max working current	500mA
Specifications of power adapter	Input:AC (50HZ, 60HZ) 100V-240V;output: DC5V/1A
Operating Temperature range	(-15 to +55)
Operating Humidity range	5 to 90%RH (No Condensation)

Dimension (L x W x H)	105x50x20mm
Weight	120g

Product diagram

Connecting operation

1. Connect 1 HDMI cable from HDMI source devices into HDMI Splitter input.
2. Connect 2 HDMI cables from displays (monitors or projectors) into the HDMI Splitter outputs.
3. Connect 5V power supply to the HDMI 1x2 Splitter.

Package Accessories

1. HDMI Splitter 1x2
- 2 Power Adapter
- 3 User Manual