

FWH-350A 500V

产品名称	FWH-350A 500V
公司名称	苏州柏幕电气有限公司
价格	面议
规格参数	品牌:COOPER BUSSMANN (EATON ' S) 型号:FWH-350A
公司地址	苏州市长吴路1号
联系电话	18120071137

产品详情

North American — FWH 500V: 35-1600A North American style stud-mount fuses

Description:

North American style high speed semiconductor stud-mount fuses.

Ratings: Volts: 500Vac/dc Amps: 35-1600A IR: 200kA Sym. 50kA@ 500Vdc Agency Information: CE, UL Recognition & CSA Component Acceptance on 35-800A only (50kA IR@500Vdc). UL Recognition on 35-1200A only, CSA Component Acceptance: 35-1600A.

Catalog Numbers

Catalog Numbers	Rated Current RMS-Amps	I ² t(A ² Sec)		Watts Loss
		Pre-arc	Clearingat 500V	
FWH-35B	35A	34	150	8
FWH-40B	40A	76	320	7.5
FWH-45B	45A	105	450	7.5
FWH-50B	50A	135	670	7.5
FWH-60B	60A	210	900	9.9
FWH-70B	70A	210	900	10.6
FWH-80B	80A	305	1400	12.7

FWH-90B	90A	360	1600	15
FWH-100B	100A	475	2000	17
FWH-125B	125A	800	3500	25
FWH-150B	150A	1100	4600	30
FWH-175B	175A	1450	6200	35
FWH-200B	200A	1900	8500	40
FWH-225A	225A	4600	23300	39
FWH-250A	250A	6300	32200	41
FWH-275A	275A	7900	40300	46
FWH-300A	300A	9800	49800	51
FWH-325A	325A	13700	63800	53
FWH-350A	350A	14500	72900	58
FWH-400A	400A	19200	96700	65
FWH-450A	450A	24700	127000	74
FWH-500A	500A	29200	149000	84
FWH-600A	600A	41300	206000	108
FWH-700A	700A	55000	298000	120
FWH-800A	800A	76200	409000	129
FWH-1000A	1000A	92000	450000	145
FWH-1200A	1200A	122000	600000	180
FWH-1400A	1400A	200000	1000000	210
FWH-1600A	1600A	290000	1400000	230

- Watts loss provided at rated current.

Features and Benefits • Excellent DC performance • Low arc voltage and low energy let-through (I2t) • Superior cycling capability

Typical Applications • DC common bus • DC drives • Power converters/rectifiers • Reduced voltage starters